

HT1015-1 1.5V Low Power LDO

Features

- Low power consumption
- · Low voltage drop
- · Low temperature coefficient

- Wide operating voltage (12V max.)
- 3-pin SOT89 and 5-pin SOT23 package

Applications

- Battery-powered equipment
- · Communication equipment


• Audio/Video equipment

General Description


The HT1015-1 is a three-terminal low power voltage regulator implemented in CMOS technology. It is available with a fixed output voltage at 1.5V. CMOS technology ensures low voltage drop and low quiescent current.

Although designed primarily as a fixed voltage regulator, this device can be used with external components to obtain variable voltages and currents.

Block Diagram



Pin Assignment





Absolute Maximum Ratings

Supply Voltage\	$V_{\rm SS}$ =0.3V to $V_{\rm SS}$ +13V	Storage Temperature	50°C to 125°C
Operating Temperature	40°C to 85°C	Maximum Junction Temperature	150°C

Note: These are stress ratings only. Stresses exceeding the range specified under "Absolute Maximum Ratings" may cause substantial damage to the device. Functional operation of this device at other conditions beyond those listed in the specification is not implied and prolonged exposure to extreme conditions may affect device reliability.

Thermal Information

Symbol	Parameter	Package	Max.	Unit
0	Thermal Resistance (Junction to Ambient)	SOT23-5	500	°C/W
θ_{JA}	(Assume no ambient airflow, no heat sink)	SOT89	200	°C/W
Pn	Dower Discipation	SOT23-5	0.20	W
- FD	Power Dissipation	SOT89	0.50	W

Note: P_D is measured at Ta= 25°C

Electrical Characteristics

Ta=25°C


Cumbal	Davamatav	Test Conditions		Min	т	N/	1114
Symbol	Parameter	V _{IN}	Conditions	Min.	Тур.	Max.	Unit
V _{OUT}	Output Voltage Tolerance	3.5V	I _{OUT} =0.5mA	1.455	1.5	1.545	V
I _{OUT}	Output Current	3.5V	_	7.0	18	_	mA
ΔV _{OUT}	Load Regulation	3.5V	1mA≤l _{OUT} ≤7mA	_	15	_	mV
V _{DIF}	Voltage Drop	_	I _{OUT} =0.5mA		250	_	mV
I _{SS}	Current Consumption	3.5V	No load	_	2.2	5.0	μА
$\frac{\Delta V_{OUT}}{\Delta V_{IN} \times V_{OUT}}$	Line Regulation		2.5V≤V _{IN} ≤12V I _{OUT} =0.5mA	_	0.1	_	%/V
V _{IN}	Input Voltage	_	_	_	_	12	V
$\frac{\Delta V_{OUT}}{\Delta T_a}$	Temperature Coefficient	3.5V	I _{OUT} =0.5mA -40°C~85°C	_	-0.75	_	mV/°C

Rev. 1.70 2 March 15, 2019




Application Circuits


Basic Circuit




High Output Current Positive Voltage Regulator



Short-Circuit Protection Using External Transistors




Increased Output Voltage Circuits




$$V_{OUT1} = V_{XX} (1 + \frac{R2}{R1}) + I_{SS} R2$$

Rev. 1.70 3 March 15, 2019






Constant Current Regulator



$$I_{OUT} = \frac{V_{XX}}{R_A} + I_{SS}$$

Dual Supply





Package Information

Note that the package information provided here is for consultation purposes only. As this information may be updated at regular intervals users are reminded to consult the <u>Holtek website</u> for the latest version of the <u>package information</u>.


Additional supplementary information with regard to packaging is listed below. Click on the relevant section to be transferred to the relevant website page.


- Further Package Information (include Outline Dimensions, Product Tape and Reel Specifications)
- Packing Meterials Information
- Carton Information

Rev. 1.70 5 March 15, 2019



3-pin SOT89 Outline Dimensions






Symbol	Dimensions in inch			
Зушьог	Min.	Nom.	Max.	
Α	0.173	_	0.181	
В	0.053	_	0.072	
С	0.090	_	0.102	
D	0.035	_	0.047	
E	0.155	_	0.167	
F	0.014	_	0.019	
G	0.017	_	0.022	
Н	_	0.059 BSC	_	
I	0.055	_	0.063	
J	0.014	_	0.017	

Symbol	Dimensions in mm			
Symbol	Min.	Nom.	Max.	
Α	4.40	_	4.60	
В	1.35	_	1.83	
С	2.29	_	2.60	
D	0.89	_	1.20	
E	3.94	_	4.25	
F	0.36	_	0.48	
G	0.44	_	0.56	
Н	_	1.50 BSC	_	
I	1.40	_	1.60	
J	0.35	_	0.44	



5-pin SOT23 Outline Dimensions



C. mb al	Dimensions in inch				
Symbol	Min.	Nom.	Max.		
Α	_	_	0.057		
A1	_	_	0.006		
A2	0.035	0.045	0.051		
b	0.012	_	0.020		
С	0.003	_	0.009		
D	_	0.114 BSC	_		
E	_	0.063 BSC	_		
е	_	0.037 BSC	_		
Н	_	0.075 BSC	_		
L	_	0.110 BSC	_		
L1	_	0.024 BSC	_		
θ	0°	_	8°		

Complete I	Dimensions in mm			
Symbol	Min.	Nom.	Max.	
А	_	_	1.45	
A1	_	_	0.15	
A2	0.90	1.15	1.30	
b	0.30	_	0.50	
С	0.08	_	0.22	
D	_	2.90 BSC	_	
E	_	1.60 BSC	_	
е	_	0.95 BSC	_	
Н	_	1.90 BSC	_	
L	_	2.80 BSC	_	
L1	_	0.60 BSC	_	
θ	0°	_	8°	

Rev. 1.70 7 March 15, 2019



Copyright $\ensuremath{\texttt{©}}$ 2019 by HOLTEK SEMICONDUCTOR INC.

The information appearing in this Data Sheet is believed to be accurate at the time of publication. However, Holtek assumes no responsibility arising from the use of the specifications described. The applications mentioned herein are used solely for the purpose of illustration and Holtek makes no warranty or representation that such applications will be suitable without further modification, nor recommends the use of its products for application that may present a risk to human life due to malfunction or otherwise. Holtek's products are not authorized for use as critical components in life support devices or systems. Holtek reserves the right to alter its products without prior notification. For the most up-to-date information, please visit our web site at http://www.holtek.com.